

Confidea L-CV

WIRED CHAIRMAN VOTING UNIT

Art. 71.98.0112

Description

The Confidea L-CV wired unit combines a slim, contemporary design with superior sound quality resulting in an excellent intelligibility.

The units are interconnected using the daisy chain principle over Cat 5 network cabling with RJ45 connectors. The connectors are hidden in the base of the unit and the cables are held in place by two notches in the unit housing.

Setup can be accomplished in just a blink of an eye.

As input or output connections are interchangeable, installation is easy, fast and straightforward, reducing installation cost. It is the ideal system for frequently changing environments.

Once installed, it allows the chairman of a conference to speak, request-to-speak, listen to the speaker and register a vote. Apart from this the prior and next-in-line buttons allow to guide the meeting.

The units are equipped with a microphone On/Off or request-to-speak button, two headphone outputs with a single volume control.

Three voting buttons are used to take part in electronic voting sessions. Results of these sessions are distributed to all participant units OLED voting result information display.



With the voting control buttons, voting sessions can be initiated, paused and ended.



For more advanced voting applications the dedicated Televic software suite can be used,



Confidea L-CV

allowing preparation of voting agenda, extended voting control, logging and result display.

A screw lock connector on the unit provides an easy way to connect a removable microphone.

As the microphone is immune against typical disturbances of mobile phones, delegates can leave their device on during the meeting. (MIC 38SL, to be ordered separately)

The Confidea L-CV can be used in combination with an RF wireless delegate unit (Confidea CV with article number 71.98.0012). The wireless conference unit has the same look and feel as the Confidea L-CV and uses a removable battery with an autonomy of 20 hours minimum.

Controls and Features

- Three voting buttons
- Voting control buttons
- OLED voting result display
- Built-in high quality loudspeaker which is automatically muted when the microphone is active, to prevent acoustic feedback.
- Microphone On/Off or request-to-speak button with two signalling LEDs
- Two headphone outputs
- One headphone volume adjustment
- PRIOR and Next-in-line buttons

Specifications

Technical Data	
Audio quality	16 bit digital
Headphone load impedance	> 32 ohm < 1k ohm
Output power	16.5 mW / 32 ohm
Power Supply	48V, over Cat5 cable
Dimensions (mm)	230(w), 130(h), 60(d)
Weight (g)	480
Color	RAL9011
Part number	Confidea L-CV 71.98.0112

Connectivity

- Two 3.5 mm jack plugs for headphones
- Two RJ45 connectors
- Screw lock socket to connect removable microphone

Accessories

- Removeable microphone MIC38SL 71.98.0050
- Headphones TEL151 71.04.0151
- Digital bus cable, Cat5 24AWG:
 - 2m ICC5/2 71.60.4002
 - 5m ICC5/5 71.60.4005
 - 10m ICC5/10 71.60.4010
 - 20m ICC5/20 71.60.4020

Standard Ethernet patch cable AWG26 cannot be used!

- SPL5525 for connection to TCS5500 central equipment 71.67.5035