



**Configuration:**

LA-207-01 12 VDC Replacement Power Supply for LT-800 (North America)\*

LA-207-02 12 VDC Replacement Power Supply for LT-800 (Asia, UK)\*

LA-207-03 12 VDC Replacement Power Supply for LT-800 (Euro)\*

LA-207-04 13 VDC Replacement Power Supply for LT-800 (Australia)\*

\*01, 02, 03, and 04 designation refers to international plug type (type B, G, C, and I) for the power supply.

**Product Overview:**

The LA-207 power supply is used to power the LT-800 Stationary Transmitter. This power supply has four different line cord configurations that can be selected by the user for their appropriate part of the world. The LA-207 is a 12 VDC power supply.

**Highlights:**

- Used to power the LT-800
- 12 VDC power supply
- Three different line cord configurations
- 90 day warranty

**Includes:**

- One (1) LA-207 12 VDC Replacement Power Supply for LT-800
- One (1) Line cord

Product Specification: 12 VDC Replacement Power Supply for LT-800	
Power	
Power Supply Type	In Line
Power Supply Input	100-240V, 50-60 Hz, 0.4A
Power Supply Output	12 VDC, 1.3A 15.6 W
Power Supply Connector	.02 in (5.0mm) OD, .01 in (2.5 mm) ID, barrel type
Physical	
Dimensions (H x W x D)	3.00 in. x 2.00 in. x 1.19 in. (76 mm x 51 mm x 30 mm)
Color	Black
Cable Length	Power Supply Cable: 6.0 ft. (183 cm) Line Cord: 6.0 ft. (183 cm)



Weight	(-01) 10.7 oz. (303 g), (-02) 12.5 oz. (354 g), (-03) 12 oz. (340 g), (-04) 12.5 oz. (354 g)
Shipping Weight	1 lb. (0.5 kg)
Compliance	
Power Supply Compliance	UL, CE, RoHS